

Features:

- No UV or IR light radiation.
- Provide 60° beam angles.
- Easy Installation:

Using Existing MR16 GU5.3 bi-pin Fixture

• Very Low Power Consumption:

Less than 3 Watts

- Long lifetime: 25000 hours (L_{70}).
- Sturdy Construction:

UV Stabilized PMMA Lens and Plastic Lamp Shell.

- High CRI: 75-85
- Correlated Color Temperature:2700-6500K
- Replaces MR16 Halogen Bulbs up to 30 Watts
- Operating temperature: $-20^{\circ}\text{C} \sim +60^{\circ}\text{C}$.
- 12V AC/DC input.
- LED type: 5630LED

Benefits

Energy Cost Savings:

Over 60% Compared to Incandescent.

Solid-State:

High-Shock & High-Vibration Resistant, Both Electrical and Mechanical

• Eco-Friendly:

No Mercury, No Lead Content

No Hazardous Emissions:

No UV or IR Radiation

Constant Light Output:

Even Lighting, Non-Halation

Application:

- Track Lighting
- Accent / Spot Lighting
- Display / Cabinet / Kiosk Lighting
- Architectural Lighting
- Art Gallery and Museum Lighting
- Other Lighting

Phone: +86-755-2518-8967

Data Sheet

Product Specifications:

Lens	PMMA		
Lamp Shell	Plastic		
Input Voltage	12V AC/DC		
Base Type	GU 5.3 Bi-Pin		
Wattage	≤3W		
Power Factor	PF≧0.7		
Operating frequency	50-60Hz		
Operating Temperature	-20°C ∽ +60°C		
Storage Temperature	-30°C ∽ +70°C		
Net Weight per piece (g)	25g		
Certification	CE Approved; RoHS Compliant		

Product Selection Guide:

Product	Beam Angle	Total Lumens	ССТ	Color	CRI
MR16-WW9R	60	280±5%	2800-3200K	Warm White	≧85
MR16-W9R	60	300±5%	5500-6500K	White	≥70

MR16-/ XX/9/R

(1)

2

(3)

4

① MR16: Product Type.

② XX: W(White) WW (Warm White)


③ 9: 9 pcs of LED


4 R: AC/DC12V input

Phone: +86-755-2518-8967

Data Sheet

Product Dimensions:






Notes:

- 1. All dimensions unit in mm
- 2. Tolerances is ± 0.5 mm unless otherwise noted.

Package Dimension



Small carton 56L*56W*94H 2.20"L*2.20"W*7.09"H 1 pcs MR16 inside

Master carton 350L*350W*315H 13.77"L*17.33"W*12.40"H 108 pcs MR16 inside

Installation Instructions and Warnings:

- Turn off power before inspection, installation, or removal.
- Not for use where exposed to the weather
- Do not use in totally enclosed fixtures.
- Not for use with dimmers.

Phone: +86-755-2518-8967

8-MAY-11© 2011luckylight